GuitarPCB Presents

NostalgiTone Bass Overthruster

This powerhouse overdrive delivers a massive range of grit and punch without sacrificing the natural character of your bass guitar or amplifier. Designed specifically to preserve low-end authority, it moves effortlessly from a bold, high-headroom clean boost to an aggressive, saturated growl while keeping your fundamental frequencies tight and powerful.

The active dual-band EQ gives you independent control over bass and treble, allowing you to shape everything from deep, powerful lows to crisp string definition. With its dynamic, touch-sensitive response and low background noise, the Bass Overthruster adds serious drive and character while keeping the natural voice of your rig intact.

🔌 Easy Wiring: No more daunting wiring hassles! Say hello to beauty under the hood. Enjoy all-analog tones with modern features that will slip into your gig bag, ensuring you are always ready to unleash your musical magic.

🛠️ Available Components: We recognize the hurdles of component availability. Rest assured, we've carefully selected components for the **NostalgiTone** series currently available from today's popular vendors.

Do not settle for the ordinary when you can have extraordinary. Elevate your tone with the **NostalgiTone** series singles from GuitarPCB. Get yours today and discover a world of sonic possibilities like never before!



Mainboard Dimensions – 2.10" x 2.12" – Perfectly sized for a 1590B or 125B enclosure

Included with each PCB purchase. – (1) Mainboard, (1) wiring board, and (1) ribbon cable.

Schematic:



Bill of Materials:

PART	VALUE
R1	2M
R2	1M
R3	10K
R4	10K
R5	180K
R6	10K
R7	10K
R8	82k
R9	10K
R10	750R

PART	VALUE
R11	2k2
R12	560R
C1	100n
C2	4u7
C3	47p
C4	100u
C5	100n
C6	100n
C7	22u

PART	VALUE
C8	100n
C9	100u
C10	2n2
C11	10n
C12	22u
D1	Status
D2	1N5817
D3	RED
D4	RED

PART	VALUE
IC1	TL072
IC2	LM833
LEVEL	A10K
GAIN	C500K
BASS	W20K
TREBLE	W20K
* CLR x1	1k8 - 4k7

BOM features Kit values. Mods are not included with Kits.

Build Notes:

Included with the purchase of the main PCB board will be (1) standard foot switch wiring board (6 pins), and (1) 6 pin ribbon cable.

There are extra IN / Out pads located at the bottom of the PCB which are conveniently placed if you wish to use side jacks.

Use a standard 6-pin ribbon cable to connect the foot switch wiring board with the main board. The 3PDT wiring board contains an onboard (CLR) current limiting resistor. This is to adjust the brightness of the corresponding main board status LEDs. A value of 1k8 to 4k7 may be used.

*** CLR x1** - Each wiring board requires an onboard (CLR) current limiting resistor. This is for the main board status LED.

Wiring Diagram





When using 1590B enclosures, it is best to mount the ribbon cable on top of the main board/3PDT wiring board instead of underneath. This is because the enclosure's compact size restricts space for the side jack Input and Output plugs.



The full-size drill templates for 125B and 1590B enclosures can be found on the following two pages. Additionally, you can find a link to Tayda's pre-drilled enclosures on the shop page at GuitarPCB.com.

This Build Document, PCB, Artwork and Schematic image are property of ©GuitarPCB.com
All copyrights, trademarks and artworks remain the property of their owners.
Any company or product names used are for identification and educational purposes only.
GuitarPCB is in no way affilliated with any said companies and are not to be misrepresented.



125B Drill Template



1590B Drill Template